

Quick Adapter for Measurement SMA-QA-JP



50Ω Adapter

Stock RoHS2

Description

The SMA-QA-JP is an Quick Adapter for Measurement . This connector is suitable for various high-frequency applications.It features a impedance 50Ω, operates up to 18GHz, and has a rated voltage of AC 500V, ensures a high insulation resistance (5000MΩ (Min.) at DC 500V), a low contact resistance (3 mΩ (Max.)), and an excellent V.S.W.R 1.3(Max.) at DC~18GHz.Withstanding temperatures from -40 to +85°C.The contact is made of Beryllium Copper/Gold Plating, while the body is Beryllium Copper/Brass/Gold Plating.We can customize our products for you. We offer total customization, including changes to a product's shape, length, material, surface treatment, and packaging.Being registered with Square and Paypal allows us to accept credit card payments from various brands.Additionally, this connector is available for purchase on Digi-Key.Available from 1 piece for in-stock items.

Specifications

Connector Gender	Plug Jack
Impedance (Ohms)	50Ω
Rated Voltage AC	AC 500V
Operating Frequency Range	18GHz
Insulation Resistance	5000MΩ (Min.) at DC 500V
Withstand Voltage	AC 1000V(1 minute)
Contact Resistance	3 mΩ (Max.)
V.S.W.R	1.3(Max.) at DC~18GHz
Operating Temperature Range	-40 to +85°C

Material/Plating/Attachment

Contact	Beryllium Copper/Gold Plating
Body	Beryllium Copper/Brass/Gold Plating

<https://www.to-conne.co.jp/en.html>

TO-CONNE CO., LTD

【Address】 5-23-11 Narimasu, Itabashi-ku
Tokyo 175-0094, Japan

TEL (+81) 3-3939-9161

MAIL overseas@to-conne.co.jp

