

BNC75Ω connector **BNCC-LA-75**



75Ω Right Angle Adapter

Stock RoHS2

### Description

The BNCC-LA-75 is an BNC75Ω Right Angle Adapter connector. This connector is suitable for various high-frequency applications. It features a impedance 75Ω, operates up to 3GHz, and has a rated voltage of AC 500V, ensures a high insulation resistance (5000MΩ (Min.) at DC 500V), a low contact resistance (3 mΩ (Max.)), and an excellent V.S.W.R 1.2 (Max.) at DC ~3000MHz. Withstanding temperatures from -40 to +85°C. The contact is made of Beryllium Copper/Gold Plating, while the body is Brass/Nickel Plating. We can customize our products for you. We offer total customization, including changes to a product's shape, length, material, surface treatment, and packaging. Being registered with Square and Paypal allows us to accept credit card payments from various brands. Additionally, this connector is available for purchase on Digi-Key. Available from 1 piece for in-stock items.

### Specifications

Connector Gender	Plug Jack
Impedance (Ohms)	75Ω
Rated Voltage AC	AC 500V
Operating Frequency Range	3GHz
Insulation Resistance	5000MΩ (Min.) at DC 500V
Withstand Voltage	AC 1500V(1 minute)
Contact Resistance	3 mΩ (Max.)
V.S.W.R	1.2 (Max.) at DC ~3000MHz
Operating Temperature Range	-40 to +85°C

### Material/Plating/Attachment

Contact	Beryllium Copper/Gold Plating
Body	Brass/Nickel Plating

<https://www.to-conne.co.jp/en.html>

**TO-CONNE CO., LTD**

【Address】 5-23-11 Narimasu, Itabashi-ku  
Tokyo 175-0094, Japan

TEL (+81) 3-3939-9161

MAIL [overseas@to-conne.co.jp](mailto:overseas@to-conne.co.jp)

