

## In/Between Series Adaptors BNCP-FJ



Mismatch Adapter

Stock RoHS2

### Description

The BNCP-FJ is an In/Between Series Adaptors . This connector is suitable for various high-frequency applications. It features a impedance Mismatch, and has a rated voltage of AC 150V, ensures a high insulation resistance (1000MΩ (Min.) at DC 500V), a low contact resistance (5 mΩ (Max.)). Withstanding temperatures from -40 to +85°C. The contact is made of Brass/Phosphor Bronze/Gold Plating, while the body is Brass/Nickel Plating. We can customize our products for you. We offer total customization, including changes to a product's shape, length, material, surface treatment, and packaging. Being registered with Square and Paypal allows us to accept credit card payments from various brands. Additionally, this connector is available for purchase on Digi-Key. Available from 1 piece for in-stock items.

### Specifications

Connector Gender	Plug Jack
Impedance (Ohms)	Mismatch
Rated Voltage AC	AC 150V
Insulation Resistance	1000MΩ (Min.) at DC 500V
Withstand Voltage	AC 500V(1 minute)
Contact Resistance	5 mΩ (Max.)
Operating Temperature Range	-40 to +85°C

### Material/Plating/Attachment

Contact	Brass/Phosphor Bronze/Gold Plating
Body	Brass/Nickel Plating

<https://www.to-conne.co.jp/en.html>

**TO-CONNE CO., LTD**

【Address】 5-23-11 Narimasu, Itabashi-ku  
Tokyo 175-0094, Japan

TEL (+81) 3-3939-9161

MAIL [overseas@to-conne.co.jp](mailto:overseas@to-conne.co.jp)

