

In/Between Series Adaptors RCAP-BNCJ



Mismatch Adapter

Stock RoHS2

Description

The RCAP-BNCJ is an In/Between Series Adaptors . This connector is suitable for various high-frequency applications.It features a impedance Mismatch, ensures a high insulation resistance (1000MΩ(Min.) at DC 500V), a low contact resistance (RCA (50mΩ(Max.)),BNC (3mΩ(Max.)).Withstanding temperatures from -40 to +85°C.The contact is made of Brass/Nickel Plating, while the body is Brass/Nickel Plating.We can customize our products for you. We offer total customization, including changes to a product's shape, length, material, surface treatment, and packaging.Being registered with Square and Paypal allows us to accept credit card payments from various brands.Additionally, this connector is available for purchase on Digi-Key.Available from 1 piece for in-stock items.

Specifications

Connector Gender	Plug Jack
Impedance (Ohms)	Mismatch
Insulation Resistance	1000MΩ (Min.) at DC 500V
Withstand Voltage	AC 500V(1 minute)
Contact Resistance	RCA (50mΩ (Max.)),BNC (3mΩ (Max.))
Operating Temperature Range	-40 to +85°C

Material/Plating/Attachment

Contact	Brass/Nickel Plating
Body	Brass/Nickel Plating

<https://www.to-conne.co.jp/en.html>

TO-CONNE CO., LTD

【Address】 5-23-11 Narimasu, Itabashi-ku
Tokyo 175-0094, Japan

TEL (+81) 3-3939-9161

MAIL overseas@to-conne.co.jp



QMS EMS
ISO 9001, JS Q 9001
ISO 14001, JS Q 14001

JAB
CM001